



Assessment of Measurement Performance for Low Field Side IDTT Plasma Position Reflectometry System

F da Silva, J Ferreira, J Santos, Stéphane Heuraux, E Ricardo, A Silva, G de Masi, O Tudisco, R Cavazzana, O d'Arcangelo

► To cite this version:

F da Silva, J Ferreira, J Santos, Stéphane Heuraux, E Ricardo, et al.. Assessment of Measurement Performance for Low Field Side IDTT Plasma Position Reflectometry System. 31st SOFT 2020, Sep 2020, Dubrovnik, Croatia. hal-02962569

HAL Id: hal-02962569

<https://hal.univ-lorraine.fr/hal-02962569>


Submitted on 12 Oct 2020

HAL is a multi-disciplinary open access archive for the deposit and dissemination of scientific research documents, whether they are published or not. The documents may come from teaching and research institutions in France or abroad, or from public or private research centers.

L'archive ouverte pluridisciplinaire **HAL**, est destinée au dépôt et à la diffusion de documents scientifiques de niveau recherche, publiés ou non, émanant des établissements d'enseignement et de recherche français ou étrangers, des laboratoires publics ou privés.

Assessment of Measurement Performance for Low Field Side IDTT Plasma Position Reflectometry System

F da Silva, J Ferreira, J Santos, ⁽¹⁾S Heuraux, E Ricardo, A Silva, ⁽²⁾G De Masi, ⁽³⁾O Tudisco, ⁽²⁾R Cavazzana and ⁽³⁾O D'Arcangelo



Instituto de Plasmas e Fusão Nuclear-Laboratório Associado, Instituto Superior Técnico, Lisboa, Portugal,

⁽¹⁾Institut Jean Lamour, UMR 7198 CNRS-Université de Lorraine, Vandoeuvre, France

⁽²⁾Consorzio RFX, 35127 Padova, Italy,

⁽³⁾Associazione EURATOM-ENEA-CR Frascati, 00044 Frascati, Italy

Summary...

- The Italian Divertor Test Tokamak (IDTT) aims to study exhaust solutions on tokamaks.
- Special look on DEMO.
- ITER is operating in detached condition. What if it proves inadequate?
- Sound alternatives must be made available.

As in all fusion machines there will be a need for diagnostics to gather knowledge about the physical processes occurring in the plasma, for engineering needs and control

Reflectometry is one of the most important techniques to diagnose fusion plasmas

Foreseen in the coming generation of machines such as ITER and DEMO.

ASSESS THE PERFORMANCE OF A PLASMA POSITION REFLECTOMETRY SYSTEM FOR IDTT OPERATING IN THE LOW FIELD SIDE

A set of 3 O-mode LFS FMCW reflectometers

On the equatorial plane gap 0°

On the upper torus midplane gap 45°

On the lower torus midplane gap -60°

ASSESSMENT MADE USING SYNTHETIC REFLECTOMETERS IMPLEMENTED USING A 2D FULL WAVE FDTD CODE

REFMUL*

Expressions for 2 & 3 Dimensions

Full polarisation e.g. REFMUL

$$\begin{aligned} \mu_0 \frac{\partial H_x}{\partial t} + \sigma^* H_y &= -\frac{\partial E_z}{\partial y} \\ \mu_0 \frac{\partial H_y}{\partial t} + \sigma^* H_x &= -\frac{\partial E_z}{\partial x} \\ \varepsilon_0 \frac{\partial E_z}{\partial t} + \sigma E_z &= -\frac{\partial H_x}{\partial y} - \frac{\partial H_y}{\partial x} \end{aligned}$$

2D TEz (X-mode) e.g. REFMULX/REFMULxp

$$\begin{aligned} \varepsilon_0 \frac{\partial E_x}{\partial t} + \sigma E_x &= -\frac{\partial H_z}{\partial y} - J_x \\ \varepsilon_0 \frac{\partial E_y}{\partial t} + \sigma E_y &= -\frac{\partial H_z}{\partial x} - J_y \\ \mu_0 \frac{\partial H_z}{\partial t} + \sigma^* H_z &= \frac{\partial E_x}{\partial y} - \frac{\partial E_y}{\partial x} \end{aligned}$$

3D Full polarisation e.g. REFMUL

$$\begin{aligned} \frac{\partial E_x}{\partial t} &= \frac{1}{\varepsilon_0} \left(\frac{\partial H_y}{\partial z} - \frac{\partial H_z}{\partial y} \right) - \frac{\sigma}{\varepsilon_0} E_x - \frac{1}{\varepsilon_0} J_x \\ \frac{\partial E_y}{\partial t} &= \frac{1}{\varepsilon_0} \left(\frac{\partial H_z}{\partial x} - \frac{\partial H_x}{\partial z} \right) - \frac{\sigma}{\varepsilon_0} E_y - \frac{1}{\varepsilon_0} J_y \\ \frac{\partial E_z}{\partial t} &= \frac{1}{\varepsilon_0} \left(\frac{\partial H_x}{\partial y} - \frac{\partial H_y}{\partial x} \right) - \frac{\sigma}{\varepsilon_0} E_z - \frac{1}{\varepsilon_0} J_z \end{aligned}$$

$$\frac{dJ_z}{dt} = \varepsilon_0 \omega_p^2 E_z + \omega_x J_y - \omega_y J_x \quad \frac{dJ_x}{dt} = \varepsilon_0 \omega_p^2 E_x - \omega_z J_y + \omega_y J_z \quad \frac{dJ_y}{dt} = \varepsilon_0 \omega_p^2 E_y + \omega_z J_x - \omega_x J_z$$

REFMUL* code family available for simulations

All REFMUL* are full-wave FDTD Maxwell codes

REFMUL: 2D O-mode simulation code

REFMULX/REFMULxp: 2D X-mode simulation codes (serial/ parallel)

REFMULF is a 2D Full polarization code

Treats all component of E (E_x, E_y, E_z) and H (H_x, H_y, H_z) of the wave

Supports a generic external magnetic field B_0 (B_{0x}, B_{0y}, B_{0z})

Couples the TE Mode (X-mode) with the TM Mode (O-mode) via J

Sources on both planes: UTS (antennas et alia...), TFSF plane wave, PBC plane wave

Extends capabilities of available 2D codes

e.g. Coupling O/X, Faraday rotation, Cotton-Mouton effect...

REFMUL3 is a 3D parallel code

All field components included

Parallel hybrid implementation (OpenMP+MPI) with 3D domain decomposition

XMDF/HDF5 compressed binary output (big data output)

Maxwell curl equations Auxiliary linear differential equation for J

FDTD most commonly applied to Maxwell's curl equations (Wave equation possible)

Usual to write the curl equation in a vacuum (with ϵ_0 and μ_0)

Condense the plasma physics in the density of current J

$$\nabla \times \mathbf{H} = \epsilon_0 \frac{\partial \mathbf{E}}{\partial t} + \sigma \mathbf{E} + \mathbf{J}$$

$$\nabla \times \mathbf{E} = -\mu_0 \frac{\partial \mathbf{H}}{\partial t} - \sigma^* \mathbf{H}$$

This results in a system coupling Maxwell equations with a LDE for $\mathbf{J} = \sigma \mathbf{E}$

$$\frac{d\mathbf{J}}{dt} = \epsilon_0 \omega_p^2 \mathbf{E} + (\omega_x + \omega_y + \omega_z) \times (\mathbf{J}_x + \mathbf{J}_y + \mathbf{J}_z)$$

The curl equations are discretised following the Yee schema

A time integrator is used to solve — the sensitive part...

Density profiles



We used an educated guess model based on the density profiles appearing in R. Martone et alia, DTT Divertor Tokamak Test facility—Interim Design Report, April 2019, using a fit on the extracted data with the expression proposed in L. Frassineti et alia, Nuclear Fusion 57 (2017) 016012.

$$\text{ntanh}^{\text{SNL}}(r) = \frac{h}{2} \left[\frac{(1 + e^{i\omega r/c})e^{-\sigma r^2}}{e^{\sigma r^2} + e^{i\omega r/c}} - \frac{(1 + s^{\text{ref}} e^{i\omega r/c})e^{-\sigma r^2}}{e^{\sigma r^2} + s^{\text{ref}} e^{i\omega r/c}} + 1 \right], \text{ with } x = \frac{p_{\text{pol}} - r}{2\Delta r}$$

Having n , as a function of real space along a line of sight, e.g. $n(r, z)$ or as a function of a flux radial variable, such as the poloidal flux $\varphi_{\text{pol}} = \psi \Psi_{\text{pol}}$, and having the 2D maps of the flux in machine coordinates (R, Z) ,

The profiles can be mapped into the machine coordinates

$$n_e(r_{\text{LOS}}) \xrightarrow{r_{\text{LOS}}(\rho_{\text{pol}})} n_e(\rho_{\text{pol}}) \xrightarrow{\rho_{\text{pol}}(R, Z)} n_e(R, Z)$$




Synthetic Diagnostics setup


Synthetic diagnostics using FDTD time-dependent codes offer a comprehensive view of reflectometry:

- Propagation in the plasma
- System location within the vacuum vessel
- Access to the plasma
- Signal processing techniques.

CAD of one of the antenna models adopted for the present work.




Synthetic reflectometer of gap 0° for Ka band operating at a frequency of 40 GHz.





Shaded part between [-0.4, -0.6] [m] in the simulation box provides a termination to the antenna giving a boundary to the oversized antenna and waveguide numerically equivalent to a well behaved transmission line.

Effects of curvature


The curvature and tilt of both plasma scenarios (SN & DN) do not introduce major deviations from the standard reference case




Full System for Gap 0° SN scenario probing



Full System for Gap 45° SN scenario probing




Profile reconstruction



The phase derivative allows us to calculate the position of a given reflecting layer r_{wall} and recover the electronic density profile using

$$r(F) = \frac{c}{2\pi^2} \int_0^F \frac{\partial \varphi}{\partial F} \frac{df}{\sqrt{F^2 - f^2}}$$

The profiles reconstructed from the phase derivatives, for the SN plasma scenario. The horizontal red line marks the separatrix density. The vertical shaded band shows the error tolerance of 1 cm in the position of the separatrix.




Phase derivative


The phase derivatives evaluated from simulation data (SN plasma scenario) represented against the theoretical WKBJ (known from input data).

The vertical red line marks the separatrix frequency. The vertical shaded areas denote the frequency ranges of the different bands.

Phase derivative 0°



Phase derivative 45°



The alignment of the antennas, optimised for the SN scenario, proved to equally performing for the DN scenario.

For the LSF reflectometers simulated, the impact of probing the plasma away from the midplane does not impose major difficulties.

Simulations of the full systems, which include the effects of the plasma and structure and their interplay, confirm a good performance with f measurement errors well within the ±1 cm error requirements, and with deviations of the order of some millimetres at the separatrix.

The main conclusion to take from this exercise is that the proposed positions (or any small variation) for the LFS are suitable for the placement of reflectometry systems and encourage to continue the efforts towards an actual implementation on IDTT.

That would be a major step for reflectometry in general, and for IDTT and DEMO in particular, since a profile measuring system away from the midplane has never been tested before.



21st Symposium on Fusion Technology

Dubrovnik (Virtual), Croatia, September 20-25, 2020

Acknowledgments: IST activities received financial support from Fundação para a Ciência e Tecnologia through project UID/FIS/50010/2013. This publication reflects the views only of the author, and European Commission cannot be held responsible for any use which may be made of the information contained therein.

