

# Comparative study of PN, PIN and new Schottky based InGaN thin films solar cells

## NanoMaterials for Energy and Environment 2016

Abdoulwahab Adaine   Sidi Hamady   Nicolas Fressengeas

Laboratoire Matériaux Optiques, Photonique et Systèmes  
Université de Lorraine & CentraleSupélec

June 2<sup>nd</sup>, 2016

# What is this all about ?

- 1 InGaN Schottky Solar Cell modeling & optimization
  - Modeling the Solar Cell
  - Multi-variate optimization
  - An optimal design
- 2 Proposal for a new InGaN MIN structure
  - Optimal PN and PIN structure
  - Schottky Based InGaN Solar Cells
  - MIN structure behavior
- 3 From simulation to realization
  - InGaN composition
  - Crystal defects
  - Metal work function
  - Future work

# And now...

## 1 InGaN Schottky Solar Cell modeling & optimization

- Modeling the Solar Cell
- Multi-variate optimization
- An optimal design

## 2 Proposal for a new InGaN MIN structure

- Optimal PN and PIN structure
- Schottky Based InGaN Solar Cells
- MIN structure behavior

## 3 From simulation to realization

- InGaN composition
- Crystal defects
- Metal work function
- Future work

# InGaN for solar cells

Decisive advantages vs. Technological issues

Continuous solar spectrum covering


- Indium composition change
- Multi-junction solar cells

Robust material

- High temperatures
- Radiation resistant

High light absorption

- Thin layers
- Nanoscale



# InGaN for solar cells

Decisive advantages vs. Technological issues

Continuous solar spectrum covering


- Indium composition change
- Multi-junction solar cells

Robust material

- High temperatures
- Radiation resistant

High light absorption

- Thin layers
- Nanoscale



# InGaN for solar cells

Decisive advantages vs. Technological issues

Continuous solar spectrum covering


- Indium composition change
- Multi-junction solar cells

Robust material

- High temperatures
- Radiation resistant

High light absorption

- Thin layers
- Nanoscale



# InGaN for solar cells

Decisive advantages vs. Technological issues

## Continuous solar spectrum covering

- Indium composition change
- Multi-junction solar cells

## Robust material

- High temperatures
- Radiation resistant

## High light absorption

- Thin layers
- Nanoscale

## Lack of lattice matched substrate

- Difficult elaboration
- High defect density

## Rough road to the device

- P doping uneasy
  - lack of acceptors
  - natural N doping
- Contact deposition difficult

# InGaN for solar cells

## Decisive advantages vs. Technological issues

## Continuous solar spectrum covering

- Indium composition change
  - Multi-junction solar cells

## Robust material

- High temperatures
  - Radiation resistant

High light absorption

- Thin layers
  - Nanoscale

#### Lack of lattice matched substrate

- Difficult elaboration
  - High defect density

## Rough road to the device

- P doping uneasy
    - lack of acceptors
    - natural N doping
  - Contact deposition difficult

# InGaN for solar cells

Decisive advantages vs. Technological issues

## Continuous solar spectrum covering

- Indium composition change
- Multi-junction solar cells

## Robust material

- High temperatures
- Radiation resistant

## High light absorption

- Thin layers
- Nanoscale

## Lack of lattice matched substrate

- Difficult elaboration
- High defect density

## Rough road to the device

- P doping uneasy
  - lack of acceptors
  - natural N doping
- Contact deposition difficult


# Optimizing the Schottky design

Removing the need for a p-layer

One junction only in this talk

- Get the best out of 1 junction
- First step towards multi-junction

## The Schottky design



UNIVERSITÉ  
DE LORRAINE

Lmops



CentraleSupélec

# Optimizing the Schottky design

Removing the need for a p-layer


One junction only in this talk

- Get the best out of 1 junction
- First step towards multi-junction

This talk objective

- p-layer free device
- Predict InGaN solar cell efficiency
- Predict the parameter set for the best efficiency
  - Dopings
  - Thicknesses
  - Metal work function

The Schottky design



# Optimizing the Schottky design

Removing the need for a p-layer


## One junction only in this talk

- Get the best out of 1 junction
- First step towards multi-junction

## This talk objective

- p-layer free device
- Predict InGaN solar cell efficiency
- Predict the parameter set for the best efficiency
  - Dopings
  - Thicknesses
  - Metal work function

## The Schottky design



# Modeling and simulation

Experimental data linked to SILVACO<sup>TM</sup> ATLAS<sup>TM</sup> 2D state of the art simulator

## Simulation framework

- ATLAS<sup>TM</sup> back-end from SILVACO<sup>TM</sup>
- 2D drift-diffusion non linear differential problem
- Coupled & decoupled methods

## InGaN parameters from experiment

- From GaN & InN binaries
- Linear Vegard interpolation for InGaN
- Bowing for affinity & bandgap: 0.8eV & 1.43eV

## Carrier Transport

- Caughey-Thomas for mobility
- Recombinations : direct, Auger, SRH and bandgap narrowing
- 1ns carrier lifetime

## Solar Light & Absorption

- Standard AM1.5 Solar Spectrum
- Adachi model
- Parameters from polynomial fit

# Modeling and simulation

Experimental data linked to SILVACO<sup>TM</sup> ATLAS<sup>TM</sup> 2D state of the art simulator

## Simulation framework

- ATLAS<sup>TM</sup> back-end from SILVACO<sup>TM</sup>
- 2D drift-diffusion non linear differential problem
- Coupled & decoupled methods

## InGaN parameters from experiment

- From GaN & InN binaries
- Linear Vegard interpolation for InGaN
- Bowing for affinity & bandgap: 0.8eV & 1.43eV

## Carrier Transport

- Caughey-Thomas for mobility
- Recombinations : direct, Auger, SRH and bandgap narrowing
- 1ns carrier lifetime

## Solar Light & Absorption

- Standard AM1.5 Solar Spectrum
- Adachi model
- Parameters from polynomial fit

# Modeling and simulation

Experimental data linked to SILVACO<sup>TM</sup> ATLAS<sup>TM</sup> 2D state of the art simulator

## Simulation framework

- ATLAS<sup>TM</sup> back-end from SILVACO<sup>TM</sup>
- 2D drift-diffusion non linear differential problem
- Coupled & decoupled methods

## InGaN parameters from experiment

- From GaN & InN binaries
- Linear Vegard interpolation for InGaN
- Bowing for affinity & bandgap: 0.8eV & 1.43eV

## Carrier Transport

- Caughey-Thomas for mobility
- Recombinations : direct, Auger, SRH and bandgap narrowing
- 1ns carrier lifetime

## Solar Light & Absorption

- Standard AM1.5 Solar Spectrum
- Adachi model
- Parameters from polynomial fit

# Modeling and simulation

Experimental data linked to SILVACO<sup>TM</sup> ATLAS<sup>TM</sup> 2D state of the art simulator

## Simulation framework

- ATLAS<sup>TM</sup> back-end from SILVACO<sup>TM</sup>
- 2D drift-diffusion non linear differential problem
- Coupled & decoupled methods

## InGaN parameters from experiment

- From GaN & InN binaries
- Linear Vegard interpolation for InGaN
- Bowing for affinity & bandgap: 0.8eV & 1.43eV

## Carrier Transport

- Caughey-Thomas for mobility
- Recombinations : direct, Auger, SRH and bandgap narrowing
- 1ns carrier lifetime

## Solar Light & Absorption

- Standard AM1.5 Solar Spectrum
- Adachi model
- Parameters from polynomial fit

# Modeling and simulation

Experimental data linked to SILVACO<sup>TM</sup> ATLAS<sup>TM</sup> 2D state of the art simulator

## Simulation framework

- ATLAS<sup>TM</sup> back-end from SILVACO<sup>TM</sup>
- 2D drift-diffusion non linear differential problem
- Coupled & decoupled methods

## InGaN parameters from experiment

- From GaN & InN binaries
- Linear Vegard interpolation for InGaN
- Bowing for affinity & bandgap: 0.8eV & 1.43eV

## Carrier Transport

- Caughey-Thomas for mobility
- Recombinations : direct, Auger, SRH and bandgap narrowing
- 1ns carrier lifetime

## Solar Light & Absorption

- Standard AM1.5 Solar Spectrum
- Adachi model
- Parameters from polynomial fit

# Simulation process

Simulation up and running : inputs and outputs

## Input data: photovoltaic cell physical parameters

- N InGaN composition, doping and thickness
- Metal work function
- In short: 4 parameters

## Simulation output data: comprehensive electrical analysis

- I-V curves
- Electric field mapping
- ...

# Simulation process

Simulation up and running : inputs and outputs

## Input data: photovoltaic cell physical parameters

- N InGaN composition, doping and thickness
- Metal work function
- In short: 4 parameters

## Simulation output data: comprehensive electrical analysis

- I-V curves
- Electric field mapping
- ...
- Cell efficiency
- Open circuit Voltage
- Short circuit Current
- PV Fill Factor

# Simulation process

Simulation up and running : inputs and outputs

## Input data: photovoltaic cell physical parameters

- N InGaN composition, doping and thickness
- Metal work function
- In short: 4 parameters

## Simulation output data: comprehensive electrical analysis

- I-V curves
- Electric field mapping
- ...
- Cell efficiency
- Open circuit Voltage
- Short circuit Current
- I-V Fill Factor

# Simulation process

Simulation up and running : inputs and outputs

## Input data: photovoltaic cell physical parameters

- N InGaN composition, doping and thickness
- Metal work function
- In short: 4 parameters

## Simulation output data: comprehensive electrical analysis

- I-V curves
- Electric field mapping
- ...
- Cell efficiency
- Open circuit Voltage
- Short circuit Current
- I-V Fill Factor

$\eta$

$V_{oc}$

$J_{sc}$

$FF$

# And now...

## 1 InGaN Schottky Solar Cell modeling & optimization

- Modeling the Solar Cell
- Multi-variate optimization
- An optimal design

## 2 Proposal for a new InGaN MIN structure

- Optimal PN and PIN structure
- Schottky Based InGaN Solar Cells
- MIN structure behavior

## 3 From simulation to realization

- InGaN composition
- Crystal defects
- Metal work function
- Future work

# The need for math

When hand driven parameter variation fails

## A multivariate optimization problem

- Efficiency is a function of 4 parameters
- Varying one parameter at a time **fails**

$$\eta : (\mathbb{R}^+)^4 \mapsto \mathbb{R}^+$$

## Various multivariate optimization methods

- Brute Force
- Gradient descent
- Conjugate gradient
- ...



UNIVERSITÉ  
DE LORRAINE

Lmops



CentraleSupélec

# The need for math

When hand driven parameter variation fails

## A multivariate optimization problem

- Efficiency is a function of 4 parameters
- Varying one parameter at a time **fails**

$$\eta : (\mathbb{R}^+)^4 \mapsto \mathbb{R}^+$$

## Various multivariate optimization methods

- Brute Force
- Gradient descent
- Conjugate gradient
- ...

# Multivariate optimization method

## SAGE/python interface to SciPy algorithms

- Formalize ATLAS™ calculations as a multivariate function
- Use the appropriate optimization method on it

## Choosing the optimization method

- Gradient and Hessian have to be approximated
- Problem bounded by physics and technology
  - Bounded approach-the gradient methods

## The question of the starting point

- Several random starting points
- To ensure maximum efficiency uniqueness

# Multivariate optimization method

## SAGE/python interface to SciPy algorithms

- Formalize ATLAS™ calculations as a multivariate function
- Use the appropriate optimization method on it

## Choosing the optimization method

- Gradient and Hessian have to be approximated
- Problem bounded by physics and technology
- **Bounded approximate gradient methods**

## The question of the starting point

- Several random starting points
- To ensure maximum efficiency uniqueness

# Multivariate optimization method

## SAGE/python interface to SciPy algorithms

- Formalize ATLAS™ calculations as a multivariate function
- Use the appropriate optimization method on it

## Choosing the optimization method

- Gradient and Hessian have to be approximated
- Problem bounded by physics and technology
- Bounded approximate gradient methods

## The question of the starting point

- Several random starting points
- To ensure maximum efficiency uniqueness

# And now...

## 1 InGaN Schottky Solar Cell modeling & optimization

- Modeling the Solar Cell
- Multi-variate optimization
- An optimal design

## 2 Proposal for a new InGaN MIN structure

- Optimal PN and PIN structure
- Schottky Based InGaN Solar Cells
- MIN structure behavior

## 3 From simulation to realization

- InGaN composition
- Crystal defects
- Metal work function
- Future work

# InGaN Schottky Solar Cell optimal design<sup>1</sup>

## Using very loose technological constraints


Optimal 18.2% efficiency with 10% tolerance

	$L_n(\mu m)$	$N_d(cm^{-3})$	$W_f(eV)$	$x$	$\eta(%)$ $V_{OC}(V)$ $J_{SC}(mA/cm^2)$ $FF(%)$
Range	$[0.10 - 1.00]$	$[1.0 \times 10^{16} - 1.0 \times 10^{19}]$	$[5.50 - 6.30]$	$[0.00 - 1.00]$	
Schottky	0.86 $[0.53 - 1.00]$	$6.5 \times 10^{16}$ $[1.0 \times 10^{16} - 3.0 \times 10^{17}]$	6.30 $[6.15 - 6.30]$	0.56 $[0.50 - 0.72]$	18.2 0.863 26.80 78.82

# Varying metal work function and composition

around the optimal values


Changing work function and composition modulates SCR



# I - V for various work functions

around the optimal values

The efficiency increase is mainly due to  $V_{OC}$  increase




# And now...

- 1 InGaN Schottky Solar Cell modeling & optimization
  - Modeling the Solar Cell
  - Multi-variate optimization
  - An optimal design
- 2 Proposal for a new InGaN MIN structure
  - Optimal PN and PIN structure
  - Schottky Based InGaN Solar Cells
  - MIN structure behavior
- 3 From simulation to realization
  - InGaN composition
  - Crystal defects
  - Metal work function
  - Future work


# InGaN PN & PIN structure optimal designs<sup>2</sup>

PN & PIN are standard structures worth optimizing

PN InGaN PV Cell



PIN InGaN PV Cell




<sup>2</sup>Superlattices and Microstructures, 2016, 96, pp.121-133.


# InGaN PN & PIN structure optimal designs

PN & PIN are standard structures worth optimizing

## PN InGaN PV Cell



## PIN InGaN PV Cell



InGaN is naturally n-doped

InGaN I layer is actually slightly N doped



# Optimal InGaN PN & PIN : 17.8% & 19% efficiency

Notice the huge 90% tolerances and the ultra-small P layer

	$L_p(\mu m)$	$L_n(\mu m)$	$N_a(cm^{-3})$	$N_d(cm^{-3})$	$x$	$\eta(\%)$ $V_{OC}(V)$ $J_{SC}(mA/cm^2)$ $FF(%)$
Range	[0.01 – 1.00]	[0.10 – 1.00]	[ $10^{16} – 10^{19}$ ]	[ $10^{16} – 10^{19}$ ]	[0.00 – 1.00]	
PN	0.01 [0.01 – 0.04]	1.00 [0.48 – 1.00]	$10^{19}$ [ $4.4 \times 10^{16} – 10^{19}$ ]	$3.9 \times 10^{16}$ [ $10^{16} – 3.5 \times 10^{17}$ ]	0.56 [0.50 – 0.72]	17.8 0.855 26.75 77.85
PIN	0.01 [0.01 – 0.04]	0.50 [0.10 – 1.00]	$10^{19}$ [ $5.9 \times 10^{16} – 10^{19}$ ]	$5.0 \times 10^{17}$ [ $1.9 \times 10^{16} – 10^{19}$ ]	0.59 [0.47 – 0.71]	19.0 0.875 27.36 79.39

- I layer optimal thickness :  $0.54\mu m$
- I layer thickness 90% tolerance :  $[0.18 – 1]\mu m$
- I layer optimal n-doping :  $5.8 \times 10^{16} cm^{-3}$
- I layer n-doping 90% tolerance :  $[10^{14} – 10^{17}]cm^{-3}$

Huge tolerances : robust device

# Optimal InGaN PN & PIN : 17.8% & 19% efficiency

Notice the huge 90% tolerances and the ultra-small P layer

	$L_p(\mu m)$	$L_n(\mu m)$	$N_a(cm^{-3})$	$N_d(cm^{-3})$	$x$	$\eta(\%)$ $V_{OC}(V)$ $J_{SC}(mA/cm^2)$ $FF(%)$
Range	[0.01 – 1.00]	[0.10 – 1.00]	[ $10^{16} – 10^{19}$ ]	[ $10^{16} – 10^{19}$ ]	[0.00 – 1.00]	
PN	0.01 [0.01 – 0.04]	1.00 [0.48 – 1.00]	$10^{19}$ [ $4.4 \times 10^{16} – 10^{19}$ ]	$3.9 \times 10^{16}$ [ $10^{16} – 3.5 \times 10^{17}$ ]	0.56 [0.50 – 0.72]	17.8 0.855 26.75 77.85
PIN	0.01 [0.01 – 0.04]	0.50 [0.10 – 1.00]	$10^{19}$ [ $5.9 \times 10^{16} – 10^{19}$ ]	$5.0 \times 10^{17}$ [ $1.9 \times 10^{16} – 10^{19}$ ]	0.59 [0.47 – 0.71]	19.0 0.875 27.36 79.39

- I layer optimal thickness :  $0.54\mu m$
- I layer thickness 90% tolerance :  $[0.18 – 1]\mu m$
- I layer optimal n-doping :  $5.8 \times 10^{16} cm^{-3}$
- I layer n-doping 90% tolerance :  $[10^{14} – 10^{17}]cm^{-3}$


Nanoscale P layer : suggests P layer removal

# Optimal InGaN PN Current-Voltage characteristics

Fixing the p-thickness and finding the optimal p-doping associated to it

For several optimal (p-thickness, p-doping) couples

PN




# Optimal InGaN PIN Current-Voltage characteristics

Fixing the p-thickness and finding the optimal p-doping associated to it

For several optimal (p-thickness, p-doping) couples

PIN



# And now...

- 1 InGaN Schottky Solar Cell modeling & optimization
  - Modeling the Solar Cell
  - Multi-variate optimization
  - An optimal design
- 2 Proposal for a new InGaN MIN structure
  - Optimal PN and PIN structure
  - Schottky Based InGaN Solar Cells
  - MIN structure behavior
- 3 From simulation to realization
  - InGaN composition
  - Crystal defects
  - Metal work function
  - Future work



UNIVERSITÉ  
DE LORRAINE

Lmops




CentraleSupélec

# Schottky Based InGaN Solar Cell<sup>2</sup>


(SBSC)

P layer removed and replaced by a Schottky contact

## Schottky InGaN PV Cell



## New Metal-IN InGaN PV Cell



<sup>2</sup>*Superlattices and Microstructures*, Elsevier, 2016, 96, pp.121-133.

A. Adaïne, S.O.S. Hamady, N. Fressengeas


PN, PIN and Schottky based InGaN solar cells (frame 16)

# Schottky Based InGaN Solar Cell

(SBSC)

P layer removed and replaced by a Schottky contact

## New Metal-IN InGaN PV Cell



InGaN is naturally n-doped

InGaN I layer is actually slightly N doped



CentraleSupélec

# Optimal InGaN Schottky & Metal-IN Solar Cells

Huge tolerances

Up to 18.2% & 19.8% efficiency

	$L_n(\mu m)$	$N_d(cm^{-3})$	$W_f(eV)$	x	$\eta(%)$ $V_{OC}(V)$ $J_{SC}(mA/cm^2)$ $FF(%)$
Range	[0.10 – 1.00]	[ $1.0 \times 10^{16}$ – $1.0 \times 10^{19}$ ]	[5.50 – 6.30]	[0.00 – 1.00]	
Schottky	0.86 [0.53 – 1.00]	$6.5 \times 10^{16}$ [ $1.0 \times 10^{16}$ – $3.0 \times 10^{17}$ ]	6.30 [6.15 – 6.30]	0.56 [0.50 – 0.72]	18.2 0.863 26.80 78.82
MIN	0.83 [0.10 – 1.00]	$3.6 \times 10^{17}$ [ $1.8 \times 10^{16}$ – $1.0 \times 10^{19}$ ]	6.30 [6.11 – 6.30]	0.60 [0.48 – 0.72]	19.8 0.835 30.29 78.39

- I layer optimal thickness :  $0.61\mu m$
- I layer thickness 90% tolerance :  $[0.1 – 1]\mu m$
- I layer optimal n-doping :  $6.1 \times 10^{16} cm^{-3}$
- I layer n-doping 90% tolerance :  $[10^{14} – 10^{17}]cm^{-3}$

# And now...

- 1 InGaN Schottky Solar Cell modeling & optimization
  - Modeling the Solar Cell
  - Multi-variate optimization
  - An optimal design
- 2 Proposal for a new InGaN MIN structure
  - Optimal PN and PIN structure
  - Schottky Based InGaN Solar Cells
  - MIN structure behavior
- 3 From simulation to realization
  - InGaN composition
  - Crystal defects
  - Metal work function
  - Future work



UNIVERSITÉ  
DE LORRAINE

LMOPS




CentraleSupélec

# InGaN Schottky and MIN Current-Voltage characteristics


$V_{OC}$  : Indium composition

$J_{SC}$ : Solar light absorption



● Schottky :  $\eta=18.2\%$ ,  $J_{SC}=26.80\text{mA}/\text{cm}^2$ ,  $V_{OC}=0.863\text{V}$ ,  $FF=78.82\%$   
▼ MIN :  $\eta=19.8\%$ ,  $J_{SC}=30.29\text{mA}/\text{cm}^2$ ,  $V_{OC}=0.835\text{V}$ ,  $FF=78.39\%$


## MIN PV efficiency as a function of the i-layer thickness



# MIN PV efficiency as a function of i-doping

for various i-thicknesses

## Optimal I-doping for optimal Space Charge Region



# And now...

- 1 InGaN Schottky Solar Cell modeling & optimization
  - Modeling the Solar Cell
  - Multi-variate optimization
  - An optimal design
- 2 Proposal for a new InGaN MIN structure
  - Optimal PN and PIN structure
  - Schottky Based InGaN Solar Cells
  - MIN structure behavior
- 3 From simulation to realization
  - InGaN composition
  - Crystal defects
  - Metal work function
  - Future work

# Optimal InGaN 0.60 composition is still difficult to achieve

Even more if several hundreds of nanometers are required

Recent (2015) experimental work reports 0.22 composition

- Limit In composition to 0.22
- Limit thickness to 400nm

Huge tolerances

7.25% efficiency

	$L_i(\mu m)$	$L_n(\mu m)$	$N_i(cm^{-3})$	$N_d(cm^{-3})$	$W_f(eV)$	$\times$	$\eta(\%)$ $V_{oc}(V)$ $J_{sc}(mA/cm^2)$ $FF(\%)$
Range	[0.10 – 0.40]	[0.10 – 0.40]	[ $1.0 \times 10^{14} – 1.0 \times 10^{17}$ ]	[ $1.0 \times 10^{16} – 1.0 \times 10^{19}$ ]	[5.50 – 6.30]	[0 – 0.22]	7.25
MIN	0.40 [0.18 – 0.40]	0.40 [0.29 – 0.40]	$6.27 \times 10^{15}$ [ $4.6 \times 10^{14} – 2.2 \times 10^{16}$ ]	$7.46 \times 10^{16}$ [ $2.0 \times 10^{16} – 1.0 \times 10^{19}$ ]	6.30 [6.20 – 6.30]	0.22 [0.19 – 0.22]	1.438 5.92 85.2

# Optimal InGaN 0.60 composition is still difficult to achieve

Even more if several hundreds of nanometers are required

Recent (2015) experimental work reports 0.22 composition

- Limit In composition to 0.22
- Limit thickness to 400nm

Huge tolerances

7.25% efficiency

	$L_i(\mu m)$	$L_n(\mu m)$	$N_i(cm^{-3})$	$N_d(cm^{-3})$	$W_f(eV)$	x	$\eta(\%)$ $V_{OC}(V)$ $J_{SC}(mA/cm^2)$ $FF(\%)$
Range	[0.10 – 0.40]	[0.10 – 0.40]	$[1.0 \times 10^{14} – 1.0 \times 10^{17}]$	$[1.0 \times 10^{16} – 1.0 \times 10^{19}]$	[5.50 – 6.30]	[0 – 0.22]	7.25
MIN	0.40 [0.18 – 0.40]	0.40 [0.29 – 0.40]	$6.27 \times 10^{15}$ $[4.6 \times 10^{14} – 2.2 \times 10^{16}]$	$7.46 \times 10^{16}$ $[2.0 \times 10^{16} – 1.0 \times 10^{18}]$	6.30 [6.20 – 6.30]	0.22 [0.19 – 0.22]	1.438 5.92 85.2

# And now...

## 1 InGaN Schottky Solar Cell modeling & optimization

- Modeling the Solar Cell
- Multi-variate optimization
- An optimal design

## 2 Proposal for a new InGaN MIN structure

- Optimal PN and PIN structure
- Schottky Based InGaN Solar Cells
- MIN structure behavior


## 3 From simulation to realization

- InGaN composition
- Crystal defects
- Metal work function
- Future work

# Efficiency degraded by crystalline defects

## Urbach tails & Gaussian distribution of defects in the band gap

Defect density must be kept lower than i-layer doping



# And now...

## 1 InGaN Schottky Solar Cell modeling & optimization

- Modeling the Solar Cell
- Multi-variate optimization
- An optimal design

## 2 Proposal for a new InGaN MIN structure

- Optimal PN and PIN structure
- Schottky Based InGaN Solar Cells
- MIN structure behavior

## 3 From simulation to realization

- InGaN composition
- Crystal defects
- Metal work function
- Future work

# Efficiency lowering with metal work function lowering

Possible defects not included

Both optimal and experimental compositions

## Zero defect efficiency with varying work function

$W_f$ (eV)	$\eta$ for $x = 0.60$ (%)	$\eta$ for $x = 0.22$ (%)
6.30	19.80	7.25
6.10	17.84	6.15
5.93	13.58	5.22
5.65	6.34	3.70

Today state of the art device realization : 3.70% efficiency

# Efficiency lowering with metal work function lowering

Possible defects not included

Both optimal and experimental compositions

## Zero defect efficiency with varying work function

$W_f$ (eV)	$\eta$ for $x = 0.60$ (%)	$\eta$ for $x = 0.22$ (%)
6.30	19.80	7.25
6.10	17.84	6.15
5.93	13.58	5.22
5.65	6.34	3.70

Today state of the art device realization : 3.70% efficiency

# And now...

## 1 InGaN Schottky Solar Cell modeling & optimization

- Modeling the Solar Cell
- Multi-variate optimization
- An optimal design

## 2 Proposal for a new InGaN MIN structure

- Optimal PN and PIN structure
- Schottky Based InGaN Solar Cells
- MIN structure behavior

## 3 From simulation to realization

- InGaN composition
- Crystal defects
- Metal work function
- Future work

# Future work

## Connect to experiments

## Contact me

- Collaborate with experimental groups
- Study their own technological constraints
- Include them in the optimization
- Realize and test the actual device
- Original approach to be adapted to other materials for PV

Details in two recently published paper

(2016)

- Numerical simulation of InGaN Schottky solar cell
- Simulation study of a new InGaN p-layer free Schottky based solar cell
- Available on ArXiv, HAL and in Elsevier journals



# Future work

Connect to experiments

Contact me

- Collaborate with experimental groups
- Study their own technological constraints
- Include them in the optimization
- Realize and test the actual device
- Original approach to be adapted to other materials for PV

Details in two recently published paper

(2016)

- Numerical simulation of InGaN Schottky solar cell
- Simulation study of a new InGaN p-layer free Schottky based solar cell
- Available on ArXiv, HAL and in Elsevier journals



CentraleSupélec

## Future work

### Connect to experiments

### Contact me

- Collaborate with experimental groups
- Study their own technological constraints
- Include them in the optimization
- Realize and test the actual device
- Original approach to be adapted to other materials for PV

### Details in two recently published paper

(2016)

- Numerical simulation of InGaN Schottky solar cell
- Simulation study of a new InGaN p-layer free Schottky based solar cell
- Available on ArXiv, HAL and in Elsevier journals



CentraleSupélec